

RF 868MHZ SYSTEM KIT FOR SHOPS



Referenzen: 5249

This radiofrequency kit allows door opening from distance remotely through a RF transmitter. The door requires a receiver that can be placed indoor (perfect for shops and/or garages) or outdoors.

The...

BESCHREIBUNG

This radiofrequency kit allows door opening from distance remotely through a RF transmitter. The door requires a receiver that can be placed indoor (perfect for shops and/or garages) or outdoors.

The transmitter has an exclusive code chosen by the user, offering the maximum security. It reaches up to 100 metres distance thanks to the frequency ratio of 868Mhz.

With the APS (Approaching System) transmission system, one can activate the button on the transmitter whilst being outside of the receptor range.

The transmitter will transmit the signal constantly until the user comes within range of the reader, when the user approximates to the door and until the door is open.

The transmitter includes 2 pushbuttons that allow to opening the door and activate a second function as turning on/off the lighting or the air conditioner, opening a second door...

The kit includes a ref. 5250 RF receiver up to 500 codes, power supply ref. 4802 and 3 Keysingle Mini transmitters ref. 5259.

TECHNISCHE DATEN

BASIC-2B

Frequency: 868,35MHz

Codification: High security changing code

Memory: 500 codes

Number of relays: 2 relay (Relay 1 (monostable) y Relay 2 (monostable/bistable))

Power Supply: 12/24Vac/dc $\pm 10\%$

Relay contacts: 1A

Consumption in standby / Consumption functioning: 60mA / 90mA

Functional temperature: -20°C to +85°C

Tightness: IP54 (IP65 with gland)



Dimensions: 63x74x25mm

Box dimensions: 82x190x40mm

Gewicht: 0,900246 kg

Maße des verpackten Produkts: 7,5x23x17,8 cm

EAN 13: 8424299052496

Enthaltene Produkte



EMITTENT RF KEYSINGLE MINI

Ref: 5259

RF Emitter with programmable security code. It allows to open doors from a distance up to 100 metres. It allows to opening doors on accesses with...

[+ INFO](#)



RECEIVER RF AXESKEY BASIC-2B 12V-24V

Ref: 5250

Autonomous receiver supplied by 12/24Vac/dc that allows to manage up to 500 codes from 868Mhz RF transmitters. A channel (emitter pushbutton) can...

[+ INFO](#)



NETZGERÄT DIN4 230VAC/12VAC-1A

Ref: 4802

Die Zuleitung kann für verschiedene Fermax-Anlagen verwendet werden.

...

[+ INFO](#)